

Power Domain

<code>create_power_domain pd1</code>	Power domain created at top level scope
<code>create_power_domain pd2 -elements cpu</code>	specify instance name
<code>create_power_domain pd3 -elements Mem -scope cpu</code>	in relative scope cpu, exists instance Mem
<code>set_domain_supply_net</code> is required to specify primary power and ground nets for a power domain	
<code>set_domain_supply_net TOP -primary_power_net VDD -primary_ground_net VSS</code>	

Power Switches - MTCMOS Cells

`create_power_switch myswitch -domain Core -input_supply_port {in VDDC} -output_supply_port {out VDDC} -control_port {Nsleep PMU/sleep} -on_state {on_state in {!sleep}}`

Place & Route later will physically map the constraint to the real switch cells:

`map_power_switch -domain <domain_name> -lib_cell <lib_cell_name> <switch_name>`

Even when not switching, CMOS cells consume leakage power. The idea is to **save leakage power by turning off design partitions when the logic is inactive**, for that, Power Switches are added between the main supply and the virtual supply to be shutdown. Of course the virtual supply is connected to standard cells supply rails.

Power Supply Network UPF 1.0

<code>create_supply_port VDD</code>	Creates Port VDD
<code>create_supply_net VDD -domain TOP</code>	Creates supply net at top level
<code>connect_supply_net VDD -ports VDD</code>	Connects supply net to port VDD

Power Supply Network UPF 1.0 (cont)

<code>set_domain_supply_net</code>	Specifies primary power/ground nets for power domain
<code>create_supply_net -reuse</code> will create supply net and supply port automatically at child level	

Level Shifters - set_level_shifter

<code>set_level_shifter LS_in -domain PD2 -applies_to inputs -rule high_to_low -location self</code>	
<code>set_level_shifter LS_out -domain PD2 -applies_to outputs -rule low_to_high -location parent</code>	
rule can be "high_to_low", "low_to_high" or "both"	location can be "self", "parent" or "automatic"

LS needed when 2 different signals belonging to different voltage power domains need to be connected to ensure proper signal value and timing propagation

Level Shifter strategy is **optional** since insertion controlled by PST. LS Strategy can be applied to control the **location** of the LS cells

ISO Cells-set_isolation/set_isolation_control

<code>set_isolation</code>	-applies_to outputs -location parent
<code>set_isolation -no_isolation -elements {list}</code>	
<code>set_isolation iso_core_out -domain Core_domain -isolation_power_net VDDC -isolation_ground_net VSS -clamp_value 1 -applies_to outputs</code>	
<code>set_isolation_control iso_core_out -domain Core_domain -isolation_signal PwrCtrl/isolate_ctrl -isolation_sense low -location parent</code>	

Provide protection during shutdown to avoid spurious signal propagation



Retention FF

```
set_retention RET_PD1 -domain PD1 -retention_power_net VDDH -retention_ground_net VSS
```

```
set_retention_control RET_PD1 -domain PD1 -save_signal {SAVE high} -restore_signal {RESTORE high}
```

```
map_retention_cell -domain PD1 -lib_cells
```

Retention FF will maintain the state of sequential elements in a shutdown block.

Retention supplies must be "Always-ON" as long as the FF need to hold their value

Power State Table - PST

Once you know more about what you are trying to define, specify the design switching characteristics in a power state table.

This requires knowing (or deciding) the operational voltages for each power domain, and the supplies being used.

The PST defines clearly **all legal voltage states and power state combinations** for a design, hence it becomes the center of the design power intent as it **captures the dynamic voltage scaling (DVS/DVFS) and shutdown scenarios**.

```
add_port_state <port_name> {-state {name <nom>}<min nom max>}<off>}}
```

Defines all possible state information to a supply port

```
create_pst <table_name> -supplies {list}
```

Creates a PST using a specific order of supply nets

```
add_pst_state <state_name> -pst <table_name> -state <supply_states>
```

Defines valid combination of supply net values for each possible state of the design

Create Block Level UPF

To specify driver supply set on input ports and receiver supply set on output port, one can use **set_port_attributes** command (SPA),

```
set_port_attributes -driver_supply_set | -receiver_supply_set VDD_set
```

To specify supply net on ports if no corresponding supply set is defined, use **set_related_supply_net**(SRSN):

```
set_related_supply_net -object_list A -power VDD
```

Idea here is to create boundary power constraints for IO ports of blocks to guide block level implementation.

Also when no SRSN/SPA is applied user can specify default supply to be used to power ports:

```
set_port_attributes -elements { . } -attribute related_supply_default_primary TRUE
```

Importance of Power State Table

Recommendation to use the supply_net names for create_pst command to keep PST matrix readable.

Power Management cell insertion is based on PST and UPF constraints:

Level shifter cells are inserted based upon the PST

Isolation cells are inserted based upon the UPF constraints

Retention cells are inserted based on constraints

Correctness of the design is checked against PST.

Always-On Logic

Some logic needs to stay active during shutdown

1-Path to enable pins of ISO/ELS

2-Power switches

3-Retention registers

4-Feedthrough paths

Always-on logic remains powered within shutdown block

1-Single-rail AO cells

2-Dual-rail AO cells

PST Example

Power State Table – Example UPF

SUPPLY	VDD	VDD_PD1	VDD_PD1S	VSS
add_port_state VDD -state {HV 1.08}	1.08	0.7	0.7	0.0
add_port_state VDD_PD1 -state {HV 1.08}	1.08	0.7	0.7	0.0
ON -state {LV 0.7}	1.08	0.7	0.7	0.0
OFF_LO	1.08	0.7	OFF	0.0
OFF_HI	1.08	1.08	OFF	0.0

Recommendation: Use meaningful state names (instead of S1, S2, S3, S4)

PST Example

Power State Table – Example UPF

```
create_pst \
dhm_pst -supplies {VDD VDD_PD1 VDD_PD1S VSS}
```

SUPPLY	VDD	VDD_PD1	VDD_PD1S	VSS
ON_LO	1.08	0.7	0.7	0.0
add_pst_state ON_LO \ -pst dhm_pst -state {HV LV LV GND}	1.08	LV	LV	GND
ON_HI	1.08	1.08	1.08	0.0
add_pst_state ON_HI \ -pst dhm_pst -state {HV HV HV GND}	1.08	HV	HV	GND
OFF_LO	1.08	0.7	OFF	0.0
add_pst_state OFF_LO \ -pst dhm_pst -state {HV LV OFF_state GND}	1.08	LV	OFF_state	GND
OFF_HI	1.08	1.08	OFF	0.0
add_pst_state OFF_HI \ -pst dhm_pst -state {HV HV OFF_state GND}	1.08	HV	OFF_state	GND



Supply Sets

`create_power_domain` doesn't require the use of `set_domain_supply_net` as pre-defined handles `primary.power` and `primary.ground` are automatically created.

Hence :

`set_isolation` doesn't require use of `-isolation_power_net` or `-isolation_ground_net` options

`set_retention` doesn't require use of `-retention_power_net` or `-retention_ground_net` options

`set_isolation -source SS_VDD1 -sink SS_VDD3 ->`

using source/sink provides finer control for inserting isolation cells to only on ports where the driver supply is related to a given supply set and load supply is related to another supply set.

Works for only for supply sets

`set_isolation -diff_supply_only true` will insert iso cells only for ports where driver and load use a different supply. Works for both supply sets and supply nets.

Supply Sets - 2 use models

Explicit: `create_supply_set mySS1 -function {power myVDD} -function {ground myVSS}`

Implicit: Supply set handles automatically created with the `create_power_domain` command

Predefined handles are : `PD1.primary PD1.default_isolation PD1.default_retention`

Supply sets provide an **abstract way of bundling supply nets** and doing the front-end implementation **without knowing the supply net and port names**. Physical net and port information is refined at the back-end. This **helps improve the re-usability of your IP since the IP is implemented without the actual nets and ports** and thus is more portable.

Complete supply network information is not needed when you do your front end implementation.

Supply Set Handles-Explicit vs Implicit

```
# Supply Set
create_power_domain PD1 -elements U1
create_supply_net PD1 -elements U1
create_supply_net SS1
create_supply_net SS1_numb1

set_domain_supply_net PD1 \
  -isolation_power_net SS1 power \
  -isolation_ground_net SS1 ground \
  -retention_power_net SS1 \
  -retention_ground_net SS1 ground
set_isolation inst1 -domain PD1 -location self \
  -source PD1 -sink SS1 \
  -power SS1_numb1.power \
  -ground SS1_numb1.ground

# Supply Set Handles
create_power_domain PD1 -elements U1
create_supply_net PD1 -elements U1
set_isolation inst1 -domain PD1 -location self \
  -source PD1.primary -sink PD1.primary
```



By **Bug Hunter** (kamezian)
cheatography.com/kamezian/

Published 26th September, 2020.
Last updated 27th September, 2020.
Page 3 of 3.

Sponsored by **Readable.com**
Measure your website readability!
<https://readable.com>