

properties of the DTFT		
Property	Aperiodic signal	FT
	$x[n], y[n]$	$X(e^{j\omega}), Y(e^{j\omega})$ period of $2\pi$
linearity	$ax[n]+by[n]$	$aX(e^{j\omega})+bY(e^{j\omega})$
time sifting	$x[n-n_0]$	$e^{-j\omega n_0}X(e^{j\omega})$
frequency shift	$e^{j\omega_0 n}x[n]$	$X(e^{j(\omega-\omega_0)})$
conjugation	$x^*[n]$	$X^*(e^{-j\omega})$
time reversal	$x[-n]$	$X(e^{j\omega})$
time expansion	$x(k)[n]=x[n/k]$ , if $n$ =multiple of $k$ 0, if $n$ ≠ multiple of $k$	$X(e^{jk\omega})$
convolution	$x[n]*y[n]$	$X(e^{j\omega})Y(e^{j\omega})$
Multiplication	$x[n]y[n]$	$\int_{-\pi}^{\pi} X(e^{j\theta})Y(e^{j(\omega-\theta)})d\theta$
differencing in time	$x[n]-x[n-1]$	$(1-e^{-j\omega})X(e^{j\omega})$
accumulation	$\sum_{k=-\infty}^n x[k]$	$(1-e^{-j\omega})^{-1}X(e^{j\omega}) + \pi \sum_{k=-\infty}^{\infty} \delta(\omega-2\pi k)$
differentiation in frequency	$nx[n]$	$J(dX(e^{j\omega}))/d\omega$

DTFT pairs		
signal	fourier tran	coefficients
$\sum_{k=-N}^N a^k e^{jk(2n/N)}$	$\sum_{k=-\infty}^{\infty} a^k \delta(\omega-N\pi k)$	$a^k$
$e^{j\omega_0 n}$	$\sum_{L=-\infty}^{\infty} \delta(\omega-\omega_0-2\pi L)$	$\omega_0=2\pi m/N$



By **bdorules**

[cheatography.com/bdorules/](http://cheatography.com/bdorules/)

Not published yet.

Last updated 3rd March, 2020.

Page 1 of 1.

Sponsored by **CrosswordCheats.com**

Learn to solve cryptic crosswords!

<http://crosswordcheats.com>