

x86 Assembly Instructions

ADD Adds <source> to <dest>. <dest> may be a register or memory. <source> may be a register, memory or immediate value.

CALL Call a function and return to the next instruction when finished. <proc> may be a relative offset from the current location, a register or memory addr.

CMP Compare <source> with <dest>. Similar to SUB instruction but does not modify the <dest> operand with the result of the subtraction.

DEC Subtract 1 from <dest>. <dest> may be a register or memory.

DIV Divide the EDX:EAX registers (64-bit combo) by <divisor>. <divisor> may be a register or memory.

INC Add 1 to <dest>. <dest> may be a register or memory.

JE Jump if Equal (ZF=1) to <loc>.

JG Jump if Greater (ZF=0 and SF=OF) to <loc>.

JGE Jump if Greater or Equal (SF=OF) to <loc>.

JLE Jump is Less or Equal (SF<>OF) to <loc>.

JMP Jump to <loc>. Unconditional.

JNE Jump if Not Equal (ZF=0) to <loc>.

JNZ Jump if Not Zero (ZF=0) to <loc>.

JZ Jump if Zero (ZF=1) to <loc>.

LEA Load Effective Address. Gets a pointer to the memory expression <source> and stores it in <dest>.

x86 Assembly Instructions (cont)

MOV Move data from <source> to <dest>. <source> may be an immediate value, register, or a memory address. Dest may be either a memory address or a register. Both <source> and <dest> may not be memory addresses.

MOVZBL Zero extend <source> to long and save in <dest>.

MUL Multiply the EDX:EAX registers (64-bit combo) by <source>. <source> may be a register or memory.

POP Take a 32-bit value from the stack and store it in <dest>. ESP is incremented by 4. <dest> may be a register, including segment registers, or memory.

PUSH Adds a 32-bit value to the top of the stack. Decrements ESP by 4. <value> may be a register, segment register, memory or immediate value.

ROL Bitwise Rotate Left the value in <dest> by <count> bits. <dest> may be a register or memory address. <count> may be immediate or CL register.

ROR Bitwise Rotate Right the value in <dest> by <count> bits. <dest> may be a register or memory address. <count> may be immediate or CL register.

SHL Bitwise Shift Left the value in <dest> by <count> bits. Zero bits added to the least significant bits. <dest> may be reg. or mem. <count> is imm. or CL.

SHR Bitwise Shift Right the value in <dest> by <count> bits. Zero bits added to the least significant bits. <dest> may be reg. or mem. <count> is imm. or CL.

x86 Assembly Instructions (cont)

SUB Subtract <source> from <dest>. <source> may be immediate, memory or a register. <dest> may be memory or a register. (source = dest)->ZF=1, (source > dest)->CF=1, (source < dest)->CF=0 and ZF=0

TEST Performs a logical OR operation but does not modify the value in the <dest> operand. (source = dest)->ZF=1, (source < dest)->ZF=0.

XCHG Exchange the contents of <source> and <dest>. Operands may be register or memory. Both operands may not be memory.

XOR Bitwise XOR the value in <source> with the value in <dest>, storing the result in <dest>. <dest> may be reg or mem and <source> may be reg, mem or imm.

What does a Linker do?

- Merges multiple relocatable (.o) object files into a single executable object file that can be loaded and executed by the loader.

- As part of the merging process, resolves external references. • External reference: reference to a symbol defined in another object file.

- Relocates symbols from their relative locations in the .o files to new absolute positions in the executable.

- Updates all references to these symbols to reflect their new positions. • References can be in either code or data

Memory Management

Info



By rwwagner90
cheatography.com/rwwagner90/

Published 23rd October, 2012.
Last updated 23rd October, 2012.
Page 1 of 1.

Sponsored by CrosswordCheats.com
Learn to solve cryptic crosswords!
<http://crosswordcheats.com>