Cheatography

systemd Cheat Sheet

by unlin via cheatography.com/75646/cs/19226/

Path

/lib/systemd/system	(Linux Mint) where you put .service files

Control an Unit

systemctl	**start [unit]**	start the unit
	stop ~	stop the unit
	status ~	show status of the unit
	restart ~	restart the unit
	enable ~	start unit on boot
	disable ~	not start unit on boot
	reload ~	reload configuration
	is-active ~	is the unit running?
	is-enabled ~	will the unit started on boot?
	mask ~	disallow the unit to start
	unmask ~	undo what **mask** does

Control Services

systemctl	**(list-units)**	list all active units
	(list-units) --all	list all units
	(list-units) --type=[type] --all	list all units of type
	daemon-reload	reload all units
	list-dependencies [unit]	list dependencies of unit
	~ [unit] --reverse	list the units depend on unit

Service File

[Unit]	Description	service name
~	Requires	e.g. network.target

By **unlin**
cheatography.com/unlin/

Not published yet.
Last updated 30th March, 2019.

Sponsored by **CrosswordCheats.com**
Learn to solve cryptic crosswords!
http://crosswordcheats.com